Portas do Firewall utilizadas na VideoConf

Essas portas precisam estar liberadas no firewall com destino os IPs: 45.236.121.15 e 45.236.121.16.

Field	Port	UDP/TCP	Effect
ng port	38000-49999	UDP	TURN Relay port Media Proxy port
	50000-60000	UDP	MCU conference port
	30000-39999	TCP	H.245/Q931 port (H.323 gateway)
	20000~24999	TCP	H.245 port (H.323 gatekeeper)
	25000~29999	TCP	Q931 port (H.323 gatekeeper)
	15000~19999	UDP	Media forwarding port (H.323 gatekeeper)
	60000~65000	UDP and TCP	Skype for Business server media port

Field	Port	UDP/TCP	Effect
System	22	TCP	SSH port
	80	TCP	HTTP port
	443	TCP	HTTPS port
	514	UDP	SYSLOG port
	514	TCP	SYSLOG port
SIP	5060	TCP	SIP port
	5060	UDP	SIP port
	5061	TCP	SIP port
	5067	TCP	Skype for Business local listening port
Turn server	3478	UDP	STUN port
	3479	UDP	STUN port
MCU broadcast service	3688	TCP	Broadcasting server listening port
WebRTC	442	TCP	WebRTC listening port
H.323 gateway	1720	TCP	H.225 listening port (TCP)
H.323 gatekeeper	1718	UDP	RAS broadcasting listening port
	1719	UDP	RAS listening port
	1722	TCP	H.225 listening port
	2776	UDP	H.460.19 RTP Multiplex port
	2777	UDP	H.460.19 RTCP Multiplex port
Media/Signali	30000-37999	UDP	IVR+BFCP port

Revision #1
Created 16 March 2020 16:36:27 by WENDEL MARCOS DOS SANTOS
Updated 16 March 2020 16:39:24 by WENDEL MARCOS DOS SANTOS